

P2 - STEERING CONTROLLER

- 1 JOYSTICK RT ROCKER SWITCH
- 2 JOYSTICK LT ROCKER SWITCH
- 3 WATER RELAY
- 4 (NOT USED)
- 5 STEERING CYL VALVES 2B
- 6 STEERING CYL VALVES 2A
- 7 STEERING CYL VALVES 3B
- 8 STEERING CYL VALVES 3A
- 9 STEERING CYL VALVES 1B
- 10 STEERING CYL VALVES 1A
- 11 12V POWER
- 12 12V POWER

- #01 BLU
- #06 BLU
- #30 RED
- #19 GRN
- #18 BLU
- #21 YEL
- #20 WHT
- #23 YEL/BLK
- #22 WHT/BLK
- #24 RED
- #25 RED

P1

- 1 GROUND
- 2 POWER
- 3 COMPUTER PLUG
- 4 COMPUTER PLUG
- 5 (NOT USED)
- 6 (NOT USED)
- 7 STEERING SEL SWITCH
- 8 SV JOYSTICK POWER
- 9 GROUND
- 10 RIGHT F/R STEER SIGNAL
- 11 L/R STEER SIGNAL
- 12 LEFT F/R STEER SIGNAL

- #36 BLK
- #26 RED
- #33 WHT
- #32 BLU
- #38 GRY
- #10 RED
- #11 BLK
- #2 GRY
- #3 WHT
- #7 GRY

W1. SEE DRAWING ART. NR. 599 05 04-01 FOR WIRE HARNESS.

A	Drawing created, by WN	JD	WN	2009-04-02
B	Redrawn to current format	MB	TE	2022-06-10
Rev.	Description	Design	Check	Date
	1		2	



This drawing is our exclusive property and is to be returned on request. It must not in any form be used to the prejudice of our interests. ©

Design By	MB
Checked By	CNI
Approved By	TG
Date	2022-06-10

Title
Wiring Diagram
Power Steer Circuit
CRT PS

Drawing2.dwg	Printed 29 June 2022 at 00:19
Items shown in this drawing must not contain substances classified as "banned" or "restricted" according to the Husqvarna Group Restricted Materials List (see www.purchase.husqvarna.com)	Sheet No 1 Of 1
Function	Article No. 599 05 04-01
Location	Rev. B